

CLP SERIES



		CLP-795GP	CLP-785	CLP-775	CLP-765GP	CLP-745	CLP-735	CLP-725	
	Stereophonic Optimizer	Yes	Yes	Yes	Yes	Yes	Yes	Yes	
Functions	Dual/Layers	Yes	Yes	Yes	Yes	Yes	Yes	Yes	
	Split	Yes	Yes	Yes	Yes	Yes	Yes	-	
	Duo	Yes	Yes	Yes	Yes	Yes	Yes	Yes	
Songs									
Preset	Number of Preset Songs	25 voice demo songs + 50 classics + 303 lesson songs	25 voice demo songs + 50 classics + 303 lesson songs	21 voice demo songs + 50 classics + 303 lesson songs	21 voice demo songs + 50 classics + 303 lesson songs	21 voice demo songs + 50 classics + 303 lesson songs	21 voice demo songs + 50 classics + 303 lesson songs	10 voice demo songs + 50 classics	
Recording	Number of Songs	250	250	250	250	250	250	1	
	Number of Tracks	16	16	16	16	16	16	2	
	Data Capacity	approx. 500 KB/Song	approx. 500 KB/Song	approx. 500 KB/Song	approx. 500 KB/Song	approx. 500 KB/Song	approx. 500 KB/Song	approx. 250 KB/Song	
Compatible Data Format	Playback	SMF (Format 0, Format 1)	SMF (Format 0, Format 1)	SMF (Format 0, Format 1)	SMF (Format 0, Format 1)	SMF (Format 0, Format 1)	SMF (Format 0, Format 1)	SMF (Format 0, Format 1)	
	Recording	SMF (Format 0)	SMF (Format 0)	SMF (Format 0)	SMF (Format 0)	SMF (Format 0)	SMF (Format 0)	SMF (Format 0)	
Functions									
Piano Room		Yes	Yes	Yes	Yes	Yes	Yes	-	
USB Audio Recorder	Playback	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	-	
	Recording	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	.wav (44.1 kHz sample rate, 16-bit resolution, stereo)	-	
Overall Controls	Metronome	Yes	Yes	Yes	Yes	Yes	Yes	Yes	
	Tempo Range	5 - 500	5 - 500	5 - 500	5 - 500	5 - 500	5 - 500	5 - 280	
	Transpose	-12 - 0 - +12	-12 - 0 - +12	-12 - 0 - +12	-12 - 0 - +12	-12 - 0 - +12	-12 - 0 - +12	-6 - 0 - +6	
	Tuning	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)
	Scale Type	7 types	7 types	7 types	7 types	7 types	7 types	-	
Rhythm		20	20	20	20	20	20	-	
Bluetooth		Audio/MIDI (varies by country)	Audio/MIDI (varies by country)	Audio/MIDI (varies by country)	Audio/MIDI (varies by country)	Audio/MIDI (varies by country)	-	-	
Storage and Connectivity									

CLP SERIES



		CLP-795GP	CLP-785	CLP-775	CLP-765GP	CLP-745	CLP-735	CLP-725
Storage	Internal Memory	Total maximum size approx. 1.4 MB	Total maximum size approx. 1.4 MB	Total maximum size approx. 1.4 MB	Total maximum size approx. 1.4 MB	Total maximum size approx. 1.4 MB	Total maximum size approx. 1.4 MB	Total maximum size approx. 960 KB (User song: One song approx. 250 KB, Loading song data from a computer: up to 10 songs)
	External Drives	USB flash drive	USB flash drive	USB flash drive	USB flash drive	USB flash drive	USB flash drive	-
Connectivity	Headphones	Standard stereo phone jack (x 2)	Standard stereo phone jack (x 2)	Standard stereo phone jack (x 2)	Standard stereo phone jack (x 2)	Standard stereo phone jack (x 2)	Standard stereo phone jack (x 2)	Standard stereo phone jack (x 2)
	MIDI	[IN] [OUT] [THRU]	[IN] [OUT] [THRU]	[IN] [OUT] [THRU]	[IN] [OUT] [THRU]	[IN] [OUT] [THRU]	[IN] [OUT] [THRU]	-
	AUX IN	Stereo Mini	Stereo Mini	Stereo Mini	Stereo Mini	Stereo Mini	Stereo Mini	-
	AUX OUT	[L/L+R] [R]	[L/L+R] [R]	[L/L+R] [R]	[L/L+R] [R]	[L/L+R] [R]	[L/L+R] [R]	-
	AUX Pedal	Yes	Yes	-	-	-	-	-
	USB TO DEVICE	Yes	Yes	Yes	Yes	Yes	Yes	-
	USB TO HOST	Yes	Yes	Yes	Yes	Yes	Yes	Yes
	DC IN	24 V	24 V	24 V	24 V	24 V	16 V	16 V
Amplifiers and Speakers								
Amplifiers		(50 W + 50 W + 50 W) x 2	(50 W + 50 W + 50 W) x 2	(42 W + 50 W + 50 W) x 2	(50 W + 42 W) x 2	(50 W + 50 W) x 2	30 W x 2	20 W x 2
Speakers		(16 cm + 8 cm + 2.5 cm (dome) + transducer) x 2, Spruce Cone Speaker	(16 cm + 8 cm + 2.5 cm (dome) + transducer) x 2, Spruce Cone Speaker	(16 cm + 8 cm + 5 cm + transducer) x 2	(16 cm + 5 cm) x 2	(16 cm + 8 cm) x 2	16 cm x 2	12 cm x 2
Power Supply								
Power Consumption		60 W (When using PA-500 AC adaptor)	60 W (When using PA-500 AC adaptor)	50 W (When using PA-500 AC adaptor)	30 W (When using PA-500 AC adaptor)	40 W (When using PA-500 AC adaptor)	18 W (When using PA-300C AC adaptor)	12 W (When using PA-300C AC adaptor)
Auto Power Off		Yes	Yes	Yes	Yes	Yes	Yes	Yes
Power Supply	Adaptors	PA-500	PA-500	PA-500	PA-500	PA-500	PA-300C	PA-300C
Accessories								
Accessories		Owner's Manual, "50 Classical Music Masterpieces" Music Book, Online Member Product Registration, Warranty*, Bench*, Power cord*/AC adaptor* PA-500 *varies by area	Owner's Manual, "50 Classical Music Masterpieces" Music Book, Online Member Product Registration, Warranty*, Bench*, Power cord*/AC adaptor* PA-500 *varies by area	Owner's Manual, "50 Classical Music Masterpieces" Music Book, Online Member Product Registration, Warranty*, Bench*, Power cord*/AC adaptor* PA-500 *varies by area	Owner's Manual, "50 Classical Music Masterpieces" Music Book, Online Member Product Registration, Warranty*, Bench*, Power cord*/AC adaptor* PA-500 *varies by area	Owner's Manual, "50 Classical Music Masterpieces" Music Book, Online Member Product Registration, Warranty*, Bench*, Power cord*/AC adaptor* PA-500 *varies by area	Owner's Manual, "50 Classical Music Masterpieces" Music Book, Online Member Product Registration, Warranty*, Bench*, Power cord*/AC adaptor* PA-300C *varies by area	Owner's Manual, "50 Classical Music Masterpieces" Music Book, Online Member Product Registration, Warranty*, Bench*, Power cord*/AC adaptor* PA-300C *varies by area